

**TABLE A-1**

**Filter Configuration Data for IF/AF Module**

Option Code	Filter BD No.	BW Type	Front Panel Display	BW No.	Filter Position	Lower Passband Freq.	Upper Passband Freq.	Offset Freq.
LA	86658	USB	2.7kHz	00	04	300	3000	0
	86659	LSB	2.7kHz	00	05	-3000	-300	0
	86662	SYM	0.3kHz	00	03	-150	150	0
	86661	SYM	1.0kHz	01	02	-500	500	0
	86658	SYM	2.7kHz	02	04	-1350	1350	-1650
	86660	SYM	6.0kHz	03	01	-3000	3000	0
	bypass	SYM	12.0kHz	04	06	-6000	6000	0
LB	86658	USB	2.7kHz	00	04	300	3000	0
	86659	LSB	2.7kHz	00	05	-3000	-300	0
	bypass	SYM	12.0kHz	04	06	-6000	6000	0
LC	86658	USB	2.7kHz	00	04	300	3000	0
	86657	USB	3.2kHz	01	05	2003	400	1800
	86658	LSB	2.7kHz	00	04	-3000	-300	-3300
	86657	LSB	3.2kHz	01	05	-3400	-200	-1800
	86662	SYM	0.3kHz	00	03	-150	150	0
	86661	SYM	1.0kHz	01	02	-500	500	0
	86658	SYM	2.7kHz	02	04	-1350	1350	-1650
	86657	SYM	3.2kHz	05	05	-1600	1600	0
	86660	SYM	6.0kHz	03	01	-3000	3000	0
	bypass	SYM	12.0kHz	04	06	-6000	6000	0
LD	86657	USB	3.2kHz	00	02	200	3400	1800
	86657	LSB	3.2kHz	00	02	-3400	-200	-1800
	86657	SYM	3.2kHz	05	02	-1600	1600	0
	86660	SYM	6.0kHz	03	01	-3000	3000	0
	bypass	SYM	12.0kHz	04	06	-6000	6000	0
LE	88115	USB	0.4kHz	00	05	1800	2200	0
	86658	USB	2.7kHz	01	04	300	3000	0
	86658	LSB	2.7kHz	00	04	-3000	-300	-3300
	86662	SYM	0.3kHz	00	03	-150	150	0
	86661	SYM	1.0kHz	01	02	-500	500	0
	86658	SYM	2.7kHz	02	04	-1350	1350	-1650
	86660	SYM	6.0kHz	03	01	-3000	3000	0
	bypass	SYM	12.0kHz	04	06	-6000	6000	0

TABLE A-1 (Continued)

Filter Configuration Data for IF/AF Module

Option Code	Filter BD No.	BW Type	Front Panel Display	BW No.	Filter Position	Lower Passband Freq.	Upper Passband Freq.	Offset Freq.
LF	88934	USB	3.1kHz	00	04	300	3400	0
	88933	LSB	3.1kHz	00	05	-3400	-300	0
	88936	SYM	0.15kHz	00	03	-75	75	0
	88937	SYM	0.3kHz	01	02	-150	150	0
	88938	SYM	0.6kHz	02	01	-300	300	0
	bypass	SYM	12.0kHz	03	06	-6000	6000	0
LG	89005	USB	1.8kHz	00	05	1100	2900	2000
	86658	USB	2.7kHz	01	04	300	3000	0
	86658	LSB	2.7kHz	00	04	-3000	-300	-3300
	88937	SYM	0.3kHz	00	03	850	1150	1000
	bypass	SYM	12.0kHz	01	06	-6000	6000	0
LH	86661	SYM	1.0kHz	3,00	2	-500	500	0
	86662	SYM	0.3kHz	3,01	3	-150	150	0
	bypass	SYM	12.0kHz	3,02	6	-6000	6000	0

**TABLE A-2**

**Filter Configuration Data for IF Filter Module**

Option Code	Rx No.	Filter BD No.	BW Type	Front Panel Display	BW No.	Filter Position	Lower Passband Freq.	Upper Passband Freq.	Offset Freq.
MB	-	87989	SYM	0.15kHz	06	07	-70	80	0
MC	-	87989	SYM	0.15kHz	06	07	-70	80	0
	-	88005	SYM	8.0kHz	07	08	-4000	4000	0
MD	1	87989	SYM	0.15kHz	06	07	-70	80	0
	1	88005	SYM	8.0kHz	07	08	-4000	4000	0
	2	87989	SYM	0.15kHz	06	10	-70	80	0
	2	88005	SYM	8.0kHz	07	11	-4000	4000	0
ME	1	87959	SYM	3.0kHz	06	7	-1500	1500	0
	2	87959	SYM	3.0kHz	06	10	-1500	1500	0
MF	-	87962	SYM	6.0kHz	06	07	-3000	3000	0
	-	87961	SYM	5.0kHz	07	08	-2500	2500	0
	-	87960	SYM	4.0kHz	08	09	-2000	2000	0
	-	87959	SYM	3.0kHz	09	10	-1500	1500	0
MG	-	87989	SYM	0.15kHz	06	07	-70	80	0
	-	87959	SYM	3.0kHz	07	08	-1500	1500	0
MH	1	87989	SYM	0.15kHz	06	07	-70	80	0
	1	88457	SYM	0.3kHz	07	08	-150	150	0
	1	88458	SYM	1.0kHz	08	09	-500	500	0
	2	87989	SYM	0.15kHz	06	10	-70	80	0
	2	88457	SYM	0.3kHz	07	11	-150	150	0
	2	88458	SYM	1.0kHz	08	12	-500	500	0
MI	1	88115	USB	0.4kHz	06	08	1800	2200	0
	1	88978	LSB	0.34kHz	06	09	-320	-660	0
	1	88939	SYM	1.5kHz	06	07	-750	750	0
	2	88115	USB	0.4kHz	06	11	1800	2200	0
	2	88978	LSB	0.34kHz	06	12	-320	-660	0
	2	88939	SYM	1.5kHz	06	10	-750	750	0
MJ	-	88935	USB	3.1kHz	06	07	300	3400	0
	-	88939	SYM	1.5kHz	06	08	-750	750	0
	-	88940	SYM	3.0kHz	07	09	-1500	1500	0
	-	88941	SYM	6.0kHz	08	10	-3000	3000	0

TABLE A-2 (Continued)

Filter Configuration Data for IF Filter Module

Option Code	Rx No.	Filter BD No.	BW Type	Front Panel Display	BW No.	Filter Position	Lower Passband Freq.	Upper Passband Freq.	Offset Freq.
MK	-	86658	USB	2.7kHz	1,06	11	300	3700	0
	-	86659	LSB	2.7kHz	2,06	12	-3000	-300	0
	-	80191	LSB	0.8kHz	2,07	10	-2220	-1420	0
	-	45250	SYM	1.0kHz	3,06	08	-500	500	0
	-	86660	SYM	6.0kHz	3,07	07	-3000	3000	0
ML	-	46715	SYM	0.1kHz		07	-50	50	0
	-	88938	SYM	0.6kHz		08	-300	300	0
MN	-	86661	SYM	1.0kHz		07	-500	500	0
	-	88939	SYM	1.5kHz		08	-750	750	0
	-	88941	SYM	6.0kHz		09	-3000	3000	0

Note: In options where Rx No. is indicated as "-" the module is intended for use in single receivers.